



## Clarity Chromatography Station – Compatibility Table

### Compatibility Table

	 Clarity	 Clarity Lite	Note
Windows 10 (32 and 64 bit)	INT7, INT9, U-PAD**, U-PAD2, Net-PAD, CB20**, Colibrick, Zebrick***	INT7, INT9, U-PAD**, U-PAD2, Colibrick	From version 6.2
Windows 8.1 (32 and 64 bit)	INT7, INT9, U-PAD**, U-PAD2, Net-PAD, CB20**, Colibrick, Zebrick***	INT7, INT9, U-PAD**, U-PAD2, Colibrick	From version 4.0.4
Windows 7 <sup>SP1</sup>	INT7, INT9, U-PAD2, Net-PAD, Colibrick*, Zebrick***	INT7, INT9, U-PAD2, Colibrick*	From version 3.0
Windows 7 <sup>SP1</sup> (32 bit)	INT7, INT9, U-PAD, U-PAD2, CB20, Net-PAD, Colibrick, Zebrick***	INT7, INT9, U-PAD, U-PAD2, Colibrick	From version 2.8
* Colibrick from version 4.0 ** U-PAD and CB20 are supported only on 32-bit versions of Windows *** Zebrick supported from Clarity 7.0 - HW Key (dongle) required for all systems from version 2.4.0 - Clarity installation may require a minimal Windows service pack version (SP) or update if specified			

### PC Configurations

	Minimal *	Recommended **
Windows 10, 8.1, 7 (32 bit, 64 bit)	PC Pentium4, 2 GB RAM	PC Pentium 4/2 GHz and newer, 4 GB RAM, SSD drive
Monitor	Resolution 1024x768 64K (16 bit High color)	Resolution 1280x1024 or 1680x1050 64K (16 bit High color)
* Minimal configuration is suitable for Clarity (Lite) configured with one Clarity Instrument running an analog acquisition using Colibrick A/D Converter ** Recommended PC requirements depend on number of Clarity Instruments and their configuration. For example running multiple Clarity Instruments simultaneously, using PDA, MS Extension and Agilent ICF control modules, pose higher demands on the processing power. Please, contact us to consult PC configuration suitable for your instrumentation. - USB port for the HW key - USB port if installed from USB Installation media - USB port for Colibrick or Zebrick - Full size PCI slot (32 bit PCI slot for 5V 32 bits half-length extension card) for INT7, INT9 or CB20; low profile or PCI Express slots cannot be used - LAN port for the Net-PAD		